



#### SURFACE MOUNT SCHOTTKY BARRIER RECTIFIERS

VOLTAGE 40 Volt CURRENT 10 Ampere

#### **FEATURES**

- Plastic package has Underwriters Laboratory Flammability Classification 94V-O
- For surface mounted applications in order to optimize board space
- · Low power loss, High efficiency
- · High surge capacity
- Lead free in compliance with EU RoHS 2011/65/EU directive
- Green molding compound as per IEC61249 Std. . (Halogen Free)

#### **MECHANICAL DATA**


Case: TO-252 molded plastic

Terminals: Solder plated, solderable per MIL-STD-750, Method 2026

Polarity: As marking

Standard packaging: 16mm tape (EIA-481) Weight: 0.0104 ounces, 0.297grams.

Marking: Part number



### MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Resistive or inductive load.


PARAMETER	SYMBOL	VALUE	UNITS
Maximum Recurrent Peak Reverse Voltage	VRRM	40	V
Maximum RMS Voltage	VRMS	28	V
Maximum DC Blocking Voltage	VR	40	V
Maximum Average Forward Current	I F(AV)	10	А
Peak Forward Surge Current : 8.3ms single half sine-wave superimposed on rated load	I FSM	200	А
Maximum Forward Voltage at 10A	VF	0.7	V
Maximum DC Reverse Current at Rated DC Blocking Voltage	I R	50	μΑ
Typical Thermal Resistance (Note 1)	Rөлс	4	°C/W
Operating Junction and Storage Temperature Range	Т <sub>J</sub> ,Тsтg	-55 to +150	°C

Note: 1. Mounted on infinite heatsink.






### **RATING AND CHARACTERISTIC CURVES**



**Fig.1 Forward Current Derating Curve** 



**Fig.2 Typical Junction Capacitance** 





Fig.3 Typical Reverse Characteristics




**Fig.4 Typical Forward Characteristics** 

PAGE . 2 November 25,2014-REV.01





### MOUNTING PAD LAYOUT



### **ORDER INFORMATION**

• Packing information

T/R - 3K per 13" plastic Reel





### Part No\_packing code\_Version

BD1040S\_L2\_00001 BD1040S\_S2\_00001

# For example:



Packing Code XX				Version Code XXXXX		
Packing type	1 <sup>st</sup> Code	Packing size code	2 <sup>nd</sup> Code	HF or RoHS	1 <sup>st</sup> Code	2 <sup>nd</sup> ~5 <sup>th</sup> Code
Tape and Ammunition Box (T/B)	Α	N/A	0	HF	0	serial number
Tape and Reel (T/R)	R	7"	1	RoHS	1	serial number
Bulk Packing (B/P)	В	13"	2			
Tube Packing (T/P)	Т	26mm	X			
Tape and Reel (Right Oriented) (TRR)	S	52mm	Y			
Tape and Reel (Left Oriented) (TRL)	L	PANASERT T/B CATHODE UP (PBCU)	U			
FORMING	F	PANASERT T/B CATHODE DOWN (PBCD)	D			





## **Disclaimer**

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
  of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
   Customers are responsible in comprehending the suitable use in particular applications.
   Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.