

DIJITAL PENSAMPERMETRE



Specifications				
Function	Max Range	Basic Accuracy	Max. Resolution	DT-3316
AC Current	2000 A	$\pm(2.5\%+5d)$	100mA	*
DC Current	2000 A	$\pm(2.5\%+5d)$	100mA	*
AC Voltage	1000V	$\pm(1.0\%+4d)$	0.1mV	*
DC Voltage	1000V	$\pm(0.5\%+4d)$	0.1mV	*
Resistance	40M Ω	$\pm(1.0\%+2d)$	0.1 Ω	*
Frequency	10MHz	$\pm(1.2\%+2d)$	0.001Hz	*
Capacitance	40mF	$\pm(3.0\%+5d)$	0.01nF	