



SURFACE MOUNT SCHOTTKY BARRIER RECTIFIER


VOLTAGE 20 to 60 Volts CURRENT 2 Amperes

FEATURES

- Plastic package has Underwriters Laboratory Flammability Classification 94V-O
- For surface mounted applications
- Metal to silicon rectifier. majority carrier conduction
- · Low power loss, high efficiency
- High surge capacity
- Lead free in comply with EU RoHS 2011/65/EU directives
- Green molding compound as per IEC61249 Std. . (Halogen Free)

MECHANICAL DATA

- Case: JEDEC DO-214AA molded plastic
- Terminals: Solder plated, solderable per MIL-STD-750, Method 2026
- Polarity: Color band denotes cathode end
- Standard packaging: 12mm tape (EIA-481)
- Weight: 0.0032 ounce, 0.092 gram



MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Resistive or inductive load.

PARAMETER	SYMBOL	SK22	SK23	SK24	SK25	SK26	UNITS
Maximum Recurrent Peak Reverse Voltage	V _{RRM}	20	30	40	50	60	V
Maximum RMS Voltage	V _{RMS}	14	21	28	35	42	V
Maximum DC Blocking Voltage	V _{DC}	20	30	40	50	60	V
Maximum Average Forward Current	I _{F(AV)}	2				Α	
Peak Forward Surge Current : 8.3ms single half sine-wave superimposed on rated load (JEDEC method)	I _{FSM}	50					А
Maximum Forward Voltage at 2A (Note 1)	V _F	0.5 0.7			.7	V	
Maximum DC Reverse Current at Rated DC Blocking Voltage T_{j} =25°C T_{j} =100°C	I _R	90 20				μA mA	
Typical Thermal Resistance (Note 2)	$R_{\theta JL}$	12					°C / W
Operating Junction Temperature Range	T _J	-55 to +125 -55 to +150			°C		
Storage Temperature Range	T _{STG}	-55 to +150			°C		

NOTES:

- 1. Pulse Test with PW =300µsec, 1% Duty Cycle.
- 2. Mounted on P.C. Board with $8\,\text{mm}^2$ (.013mm thick) copper pad areas.





RATING AND CHARACTERISTIC CURVES




Fig.1- FORWARD CURRENT DERATING CURVE




Fig.2- MAXIMUM NON-REPETITIVEPEAKFORWARD SURGE CURRENT




Fig.3-TYPICAL REVERSE CHARACTERISTIC





Fig.4-TYPICAL INSTANTANEOUS FORWARD CHARACTERISTIC





MOUNTING PAD LAYOUT



ORDER INFORMATION

• Packing information

T/R - 3K per 13" plastic Reel

T/R - 0.5K per 7" plastic Reel





Part No_packing code_Version

SK22_R1_00001 SK22_R2_00001

For example:



Packing Code XX					Version Code XXXXX			
Packing type	1 st Code	Packing size code	2 nd Code	HF or RoHS	1 st Code	2 nd ~5 th Code		
Tape and Ammunition Box (T/B)	Α	N/A	0	HF	0	serial number		
Tape and Reel (T/R)	R	7"	1	RoHS	1	serial number		
Bulk Packing (B/P)	В	13"	2					
Tube Packing (T/P)	Т	26mm	Х					
Tape and Reel (Right Oriented) (TRR)	S	52mm	Y					
Tape and Reel (Left Oriented) (TRL)	L	PANASERT T/B CATHODE UP (PBCU)	U					
FORMING	F	PANASERT T/B CATHODE DOWN (PBCD)	D					





Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
 of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
 Customers are responsible in comprehending the suitable use in particular applications.
 Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.