

Damping

Ordering code: B25835 Date: September 2005

© EPCOS AG 2005. Reproduction, publication and dissemination of this data sheet, enclosures hereto and the information contained therein without EPCOS' prior express consent is prohibited.

Damping

Features

- High dielectric strength
- High peak-current capability

Applications

Especially suitable for snubber circuits

Construction

- Self-healing
- Plastic dielectric
- Oil-impregnated tubular windings (no PCB)
- Metal-sprayed end faces ensure reliable contacting
- Cylindrical aluminum case
- 1-pole version, ceramic lead-through
- Mounting bolts M8 or M12

Terminals

Tab connector 6.3 mm

Mounting

If the vibration stress is $\leq 5 g$ the bolt is used for mounting.

Grounding

1-pole capacitors need not be grounded.

Individual data sheets

Individual data sheets contain detailed specification incl. thermal data. Upon request, these data sheets are available for each capacitor type.





Damping

Technical data

Standards		IEC 1071-1/2
		EN 61071-1/2
		VDE 0560 part 120 and 121
Dielectric dissipation factor	tan δ_0	2 · 10 ⁻⁴
Capacitance tolerance		± 10%
Max. repetitive rate		î
of voltage rise	(dv/dt) _{max}	ō
Max. non-repetitive rate of voltage rise	(dv/dt) _s	
Climatic data:	(/3	
Min. operating temperature	T _{min}	– 25 °C
Max. operating temperature	T _{max}	+ 85 °C
Average relative humidity		≤ 95%
Failure quota	$\alpha_{FQ(co)}$	300 failures per 10 ⁹ component hours
Load duration	t _{LD(co)}	100 000 h
Storage temperature limit	T _{stg}	– 55/+ 85 °C
IEC climatic category (IEC 68-1 and 2)	-	25/085/56
Test data:		
AC test voltage between terminals	V _{TT}	1.25 x V _R , 50 Hz, 10 s (or DC 1.75 x V _R , 10 s)
Insulation resistance	R _{ins}	$C_R \le 1 \ \mu F: \ge 10\ 000\ M\Omega$
Self-discharge time constant	$\tau = R_{ins} \times C$	$C_R > 1 \ \mu F: \ge 10\ 000\ s$
Dissipation factor (50 Hz)	tan δ	$\leq 3 \cdot 10^{-4}$



Damping

Characteristics and ordering codes

$ \begin{array}{c c c c c c c c c c c c c c c c c c c $) s				
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$)s				
nnnnn0.22109022015.011025 × 57140B25835M6224K0070.331013033011.011025 × 57140B25835M6334K0070.471010025019.011025 × 57140B25835M6474K0070.681815037014.011030 × 57150B25835M6684K0071.001822055010.011030 × 57150B25835M6105K0072.201848012006.611045 × 571110B25835M6225K0074.7018100025004.611060 × 571190B25835M6475K007V $\hat{v} = 1800 V$ $\hat{v}_s = 2400 V$ $V_{TT} = AC 1800 V, 1$ 0.101015038020.011025 × 57240B25835M0104K0070.221022055018.014025 × 70150B25835M0224K0070.331020050027.019025 × 95160B25835M0334K007)s				
$\begin{array}{c ccccccccccccccccccccccccccccccccccc$					
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$					
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$					
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$					
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$					
4.7018100025004.6110 60×57 1190B25835M6475K007 $V_{\rm R} = AC$ 1400 V $\hat{v} = 1800$ V $v_{\rm s} = 2400$ V $V_{\rm TT} = AC$ 1800 V, 10.101015038020.011025 \times 57240B25835M0104K0070.221022055018.014025 \times 70150B25835M0224K0070.331020050027.019025 \times 95160B25835M0334K007					
$V_{\rm R} = AC 1400 V$ $\hat{v} = 1800 V$ $v_{\rm s} = 2400 V$ $V_{\rm TT} = AC 1800 V, 1$ 0.101015038020.011025 × 57240B25835M0104K0070.221022055018.014025 × 70150B25835M0224K0070.331020050027.019025 × 95160B25835M0334K007					
0.10 10 150 380 20.0 110 25 × 57 2 40 B25835M0104K007 0.22 10 220 550 18.0 140 25 × 70 1 50 B25835M0224K007 0.33 10 200 500 27.0 190 25 × 95 1 60 B25835M0334K007					
0.22 10 220 550 18.0 140 25 × 70 1 50 B25835M0224K007 0.33 10 200 500 27.0 190 25 × 95 1 60 B25835M0334K007)s				
0.33 10 200 500 27.0 190 25×95 1 60 B25835M0334K007					
0.47 18 280 700 20.0 190 30×95 1 90 B25835M0474K007					
0.68 18 400 1000 15.0 190 30×95 1 90 B25835M0684K007					
1.00 18 600 1500 12.0 190 35 × 95 1 110 B25835M0105K007					
2.20 18 1300 3300 7.6 190 50×95 1 220 B25835M0225K007					
$V_{R} = AC 1700 V$ $\hat{v} = 2100 V$ $v_{s} = 2900 V$ $V_{TT} = AC 2100 V$, 1					
0.10 10 200 500 16.0 110 25×57 2 40 B25835M7104K007					
0.22 10 300 750 15.0 140 25×70 1 50 B25835M7224K007					
0.47 18 660 1600 8.4 140 35 × 70 1 90 B25835M7474K007					

1) Other capacitance values upon request



Damping

Characteristics and ordering codes

$\overline{C_R^{1)}}$	I _{max}	î	۱ _s	R _S 20 °C	L _{self}	$\begin{array}{c} \text{Dimensions} \\ \text{d} \times \text{I} \end{array}$	Fig.	Appr. weight	Ordering code
μF	А	А	А	mΩ	nH	mm		g	
V _R = A	C 2100	V V	Ń) = 260	0 V	v _s =	3600	V	V _{TT} = AC 2600 V, 10 s
0.47	18	750	1900	11.0	190	35× 95	2	110	B25835M1474K007
0.68	18	1100	2700	8.7	190	40× 95	1	140	B25835M1684K007
1.00	18	1600	4000	7.1	190	45× 95	1	180	B25835M1105K007
2.20	18	1100	2800	13.0	250	60 × 131	1	440	B25835M1225K007
$V_{N} = AC 3400 V$ $\hat{v} = 4300 V$ $v_{s} = 5800 V$ $V_{TT} = AC 4300$					V _{TT} = AC 4300 V, 10 s				
0.10	18	280	700	33.0	250	35 imes 131	1	150	B25835M2104K007
0.15	18	400	1000	24.0	250	35 imes 131	1	150	B25835M2154K007
0.22	18	600	1500	18.0	250	35 imes 131	1	150	B25835M2224K007
0.33	18	900	2300	15.0	250	50 imes 131	1	300	B25835M2334K007
0.47	18	1300	3300	12.0	250	50 imes 131	1	300	B25835M2474K007
0.68	18	1900	4800	11.0	250	60 × 131	1	440	B25835M2684K007


¹⁾ Other capacitance values upon request



Damping

B25835

Dimensional drawing



d +0.5	+1 -2	I ₁ +1*)	I _{2max}	Creepage	Clear-
				distance	ance
mm	mm	mm	mm	mm	mm
25	57	8	15	6	6
25	57	8	23	14	14
25	70	8	23	14	14
25	95	8	23	14	14
30	57	8	15	6	6
30	95	8	23	14	14
35	70	8	26	14	14
35	95	8	26	14	14
35	95	8	32	20	20
35	131	8	32	20	20
40	95	8	32	20	20
45	57	8	22	10	10
45	95	8	32	20	20
50	95	12	26	14	14
50	131	12	32	20	20
60	57	12	22	10	10
60	131	12	32	20	20

*) 8 mm =threaded bolt M8 12 mm =threaded bolt M12

Mounting parts (included in delivery)

Threaded bolt	Max. torque	Washer	Hex nut
M8	4 Nm	A 8.4 DIN 125-Ms	M 8 DIN 439
M12	10 Nm	A 13 DIN 125-Ms	M12 DIN 439

Please read Cautions and warnings and Important notes at the end of this document. 6 09/05



Damping

Cautions and warnings

Safety

- In case of dents of more than 1 mm depth or any other mechanical damage, capacitors must not be used at all. This applies also in cases of oil leakage.
- Electrical or mechanical misapplication of capacitors may be hazardous. Personal injury or property damage may result from bursting of the capacitor or from expulsion of oil or melted material due to mechanical disruption of the capacitor.
- Ensure good, effective grounding for capacitor enclosures.
- Observe appropriate safety precautions during operation (self-recharging phenomena and the high energy contained in capacitors).
- Handle capacitors carefully, because they may still be charged even after disconnection.
- The terminals of capacitors, connected bus bars and cables as well as other devices may also be energized.
- Follow good engineering practice.
- Failure to follow cautions may result, worst case, in premature failures, bursting and fire.

Thermal load

After installation of the capacitor it is necessary to verify that maximum hot-spot temperature is not exceeded at extreme service conditions (see www.epcos.com/thermal_design).

Mechanical protection

The capacitor has to be installed in a way that mechanical damages and dents in the aluminum can are avoided.

Storage and operating conditions

Do not use or store capacitors in corrosive atmosphere especially where chloride gas, sulfide gas, acid, alkali, salt or the like are present. In dusty environments, regular maintenance and cleaning especially of the terminals is required to avoid conductive path between phases and/or phases and ground.

Overpressure disconnector

To ensure full functionality of an overpressure disconnector, the following must be observed:

- The elastic elements must not be hindered, i.e.
 - connecting lines must be flexible leads (cables),
 - there must be sufficient space (minimum 12 mm) above the connections for expansion of the overpressure disconnector,
 - folding crimps must not be retained by clamps.
- Stress parameters of the capacitor must be within the IEC61071 specification.

Service life expectancy

Electrical components do not have an unlimited service life expectancy; this applies to self-healing capacitors too. The maximum service life expectancy may vary depending on the application the capacitor is used in.

7 09/05



The following applies to all products named in this publication:

- Some parts of this publication contain statements about the suitability of our products for certain areas of application. These statements are based on our knowledge of typical requirements that are often placed on our products in the areas of application concerned. We nevertheless expressly point out that such statements cannot be regarded as binding statements about the suitability of our products for a particular customer application. As a rule, EPCOS is either unfamiliar with individual customer applications or less familiar with them than the customers themselves. For these reasons, it is always ultimately incumbent on the customer to check and decide whether an EPCOS product with the properties described in the
- 2. We also point out that in individual cases, a malfunction of passive electronic components or failure before the end of their usual service life cannot be completely ruled out in the current state of the art, even if they are operated as specified. In customer applications requiring a very high level of operational safety and especially in customer applications in which the malfunction or failure of a passive electronic component could endanger human life or health (e.g. in accident prevention or life-saving systems), it must therefore be ensured by means of suitable design of the customer application or other action taken by the customer (e.g. installation of protective circuitry or redundancy) that no injury or damage is sustained by third parties in the event of malfunction or failure of a passive electronic component.
- 3. The warnings, cautions and product-specific notes must be observed.

product specification is suitable for use in a particular customer application.

- 4. In order to satisfy certain technical requirements, some of the products described in this publication may contain substances subject to restrictions in certain jurisdictions (e.g. because they are classed as "hazardous"). Useful information on this will be found in our Material Data Sheets on the Internet (www.epcos.com/material). Should you have any more detailed questions, please contact our sales offices.
- 5. We constantly strive to improve our products. Consequently, **the products described in this publication may change from time to time**. The same is true of the corresponding product specifications. Please check therefore to what extent product descriptions and specifications contained in this publication are still applicable before or when you place an order.

We also **reserve the right to discontinue production and delivery of products**. Consequently, we cannot guarantee that all products named in this publication will always be available.

- 6. Unless otherwise agreed in individual contracts, all orders are subject to the current version of the "General Terms of Delivery for Products and Services in the Electrical Industry" published by the German Electrical and Electronics Industry Association (ZVEI).
- 7. The trade names EPCOS, CeraDiode, CSSP, PhaseCap, PhaseMod, SilverCap, SIFI, SIMID, SIKOREL, SIOV, SIP5D, SIP5K, TOPcap, UltraCap, WindCap are trademarks registered or pending in Europe and in other countries. Further information will be found on the Internet at www.epcos.com/trademarks.