



Connector: SMA Plug (Male Pin)				
Termination: Cable End Crimp				
Part Number		CONSMA007	CONSMA007-G	
Connector Part	Material	Finish	Finish	
Bodies	Body: Brass	Nickel	Gold	
	Crimp Ring: Brass	Nickel	Gold	
Center Contact	Pin: Brass	Gold	Gold	
Insulator	PTFE	_	_	
Gasket	Silicone Rubber	_	_	
Heat Shrink	Polyolefin	_	_	

REVISIONS				
REV	DESCRIPTION	DATE	APPV	
A INITIAL RELEASE OF LINX INTERNAL DRAWING 01/MAR/19 C		CLL		









SCALE 2:1

NOTES: (UNLESS OTHERWISE SPECIFIED)

- 1. ALL DIMENSIONS ARE IN mm [INCHES].
- 2. DIMENSIONS APPLY AFTER FINISHING.
- 3. MANUFACTURE TO BE COMPLIANT WITH EU ROHS DIRECTIVE, USE MATERIALS THAT DO NOT CONTAIN REACH SUBSTANCES OF VERY HIGH CONCERN >1000ppm, AND USE DRC CONFLICT-FREE SOURCED MATERIALS.
- 4. SAFETY BREAK ALL SHARP CORNERS AND EDGES 0.5 MAXIMUM.
- SEE TABLE I FOR ELECTRICAL SPECIFICATIONS. (SHEET 2)
- 6 SEE TABLE II FOR ENVIRONMENTAL SPECIFICATIONS. (SHEET 2)
- SEE TABLE III FOR MECHANICAL SPECIFICATIONS. (SHEET 2)
- 8. SEE PARTSLIST. "*" INDICATES FINISH TYPE.

SCALE 1:1

WARNING: THIS DRAWING CONTAINS PROPRIETARY INFORMATION THAT IS THE SOLE PROPERTY OF LINX TECHNOLOGIES, AND SHALL BE TREATED AS SUCH. NO DISCLOSURE OR REPRODUCTION OF THIS DOCUMENT IS PERMITTED, IN WHOLE OR IN PART, WITHOUT THE **EXPRESS WRITTEN PERMISSION OF LINX TECHNOLOGIES OR ITS** DESIGNATED AGENTS.

MATERIAL: PROJECTION: TOLERANCES: 0.50 [.020]-5.00 [.200]=±0.20 [.008] 5.00 [.200]-30.00 [1.200]=±0.40 [.016] 30.0 [1.20]-120.0 [4.75]=±0.60 [0.24] 120.0 [4.75]-315.0 [12.40]=±1.0 [.040] \oplus ANGLES: ±1 FINISH: DRAWN: M. SCHULTE

DT: 21/JAN/19 ENGR: D. VARATHARAJAN DT: 08/MAR/19

159 ORT LANE **MERLIN, OR 97532**

SMA MALE CABLE END CRIMP FOR RG-174 CABLE

SIZE DWG. NO. REV CONSMA007-* Α SCALE: 3:1 SHEET 1 OF 2 DO NOT SCALE DRAWING

5 TABLE I

Electrical Data	Detail
Impedance	50 Ω
Frequency Range	0 to 18 GHz
Insulation Resistance	5 000 M Ω min.
Voltage Rating	1 000 V RMS
Contact Resistance	Center: $\leq 3.0 \text{ m}\Omega$ Outer: $\leq 2.5 \text{ m}\Omega$
VSWR: f (GHz)	RG-174, or Equivalent 1.15+0.02f
Working Voltage	RG-174, or Equivalent → 335 V RMS max.
Dielectric Withstanding Voltage	RG-174, or Equivalent → 750 V RMS max.

6 TABLE II


Environmental Data	Detail
Corrosion (Salt spray)	ASTM B-117
Thermal Shock	MIL-STD-202 Method 107 test condition B
Vibration	MIL-STD-202 Method 204 test condition D
Mechanical Shock	MIL-STD-202 Method 213 test condition I
Temperature Range	-55 °C to +155 °C
Environmental Compliance	RoHS

7 TABLE III

Mechanical Data	Detail
Mounting Type	Free Hanging (In-Line)
Fastening Type	1/4"-36 Threaded Coupling
Recommended Torque	0.57 N·m (5.0 in·lbs)
Coupling Nut Retention	60 lbs. min.
Connector Durability	500 cycles min.
Weight	3 g (0.1 oz)

ASSEMBLY INSTRUCTIONS

- 1. Strip the cable to the recommended dimensions.
- 2. Slip heat shrink and crimp ring onto stripped cable.
- 3. Solder the pin to the center-conductor.
- 4. Insert the pin, center-conductor and insulator into the body until the top of the pin is flush with the opening of the body.
- 5. Wrap the braid around the tail of the body and crimp the ring with a 0.128" hex crimp tool, (or one labeled for use with RG-174 cable).
- 6. Use heat shrink to cover crimp.



RECOMMENDED CABLE STRIPPING DIMENSIONS CAN ALSO BE USED WITH: RG-188A & RG-316