# EVERLIGHT ELECTRONICS CO.,LTD.

#### **Technical Data Sheet**

# **Reverse Package Chip LED**

#### 24-21UYC/S530-A3/TR8

#### **Features**

- Package in 8mm tape on 7" diameter reel.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow solder process.
- Mono-color type.
- Pb-free
- The product itself will remain within RoHS complaint version




- The 24-21 SMD LED is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.
- Besides, lightweight makes them ideal for miniature applications. etc.

#### **Applications**


- Backlighting in dashboard and switch.
- Telecommunication: indicator and backlighting in telephone and fax.
- Flat backlight for LCD, switch and symbol.
- General use.


#### **Device Selection Guide**


D. AN.	Chip	F - '44 1 C 1	Resin Color	
Part No.	Material	Emitted Color		
24-21UYC/S530-A3/TR8	AlGaInP	Brilliant Orange	Water Clear	



## **Package Outline Dimensions**







**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm ,Unit = m

Rev 1 Page: 2 of 9

#### **Absolute Maximum Ratings (Ta=25°C)**

Parameter	Symbol	Rating	Unit	
Reverse Voltage	$V_R$	5	V	
Forward Current	$I_{F}$	25	mA	
Operating Temperature	$I_{FP}$	60	mA	
Storage Temperature	Pd	60	mW	
Electrostatic Discharge (HBM)	ESD	2000	V	
Power Dissipation	Topr	<b>-</b> 40 ∼ +85	$^{\circ}\!\mathbb{C}$	
Peak Forward Current (Duty 1/10 @1KHz)	Tstg	-40 ~ +90	$^{\circ}$	
Soldering Temperature	Tsol	Reflow Soldering : 260 °C for 10 sec.  Hand Soldering : 350 °C for 3 sec.		

## **Electro-Optical Characteristics (Ta=25°C)**

Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Luminous Intensity	$I_{v}$	38	59		mcd		
Viewing Angle	201/2		130		deg		
Peak Wavelength	$\lambda_{ m p}$		591		nm	I -20m A	
Dominant Wavelength	$\lambda_{ m d}$		589		nm	$I_{\rm F}$ =20mA	
Spectrum Radiation Bandwidth	Δλ		15		nm		
Forward Voltage	$V_{\mathrm{F}}$	1.70	2.0	2.40	V		
Reverse Current	$I_R$			10	μΑ	$V_R=5V$	

#### **Notes:**

1.Tolerance of Luminous Intensity ±11%

2.Tolerance of Dominant Wavelength ±1nm

Everlight Electronics Co., Ltd. Device No:SZDSE-241-

http://www.everlight.com Prepared date: 8-Apr-2009


Prepared by: Huang yongxin


Rev 1 Page: 3 of 9


# EVERLIGHT ELECTRONICS CO.,LTD.


#### 24-21UYC/S530-A3/TR8


#### **Typical Electro-Optical Characteristics Curves**


















#### Label explanation


**CAT: Luminous Intensity Rank** 

**HUE: Dom. Wavelength Rank** 

**REF: Forward Voltage Rank** 



#### **Reel Dimensions**




**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm ,Unit = mm

Rev 1 Page: 5 of 9


Prepared date: 8-Apr-2009

## Carrier Tape Dimensions: Loaded quantity 2000 PCS per reel



**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm ,Unit = mm

## **Moisture Resistant Packaging**



Everlight Electronics Co., Ltd. Device No:SZDSE-241-

http://www.everlight.com Prepared date: 8-Apr-2009 Rev 1 Page: 6 of 9

Prepared by: Huang yongxin

## **Reliability Test Items And Conditions**

The reliability of products shall be satisfied with items listed below.

Confidence level: 90%

LTPD: 10%

No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260°C±5°C Min 5 sec. 6 Min.		22 Pcs.	0/1
2	Temperature Cycle	H:+100°C 15min  ∫ 5 min  L:-40°C 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	H: $+100^{\circ}$ C 5min $\int 10 \sec$ L: $-10^{\circ}$ C 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100°C	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40°℃	1000 Hrs.	22 PCS.	0/1
6	DC Operating Life	$I_F = 20 \text{ mA}$	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85°C/85% RH	1000 Hrs.	22 PCS.	0/1

Prepared by: Huang yongxin


Rev 1 Page: 7 of 9

#### **Precautions For Use**

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

- 2. Storage
- 2.1 Do not open moisture proof bag before the products are ready to use.
- 2.2 Before opening the package, the LEDs should be kept at 30°C or less and 90%RH or less.
- 2.3 After opening the package: The LED's floor life is 1 year under 30°C or less and 60% RH or less. If unused LEDs remain, it should be stored in moisture proof packages.
- 2.4 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions. Baking treatment : 60±5°C for 24 hours.
- 3. Soldering Condition
- 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

Prepared date: 8-Apr-2009

Prepared by: Huang yongxin

Rev 1 Page: 8 of 9




#### 4. Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than  $350^{\circ}$ C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

#### 5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



EVERLIGHT ELECTRONICS CO., LTD.

Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C Tel: 886-2-2267-2000, 2267-9936

Fax: 886-2267-6244, 2267-6189, 2267-6306

http://www.everlight.com

http://www.everlight.com

Prepared date: 8-Apr-2009 Prepare

Rev 1 Page: 9 of 9

Prepared by: Huang yongxin