

# TOOLFIX TF 101

## DİJİTAL ÖLÇÜ ALETİ



TEKNİK ÖZELLİK	ARALIK	DOĞRULUK
DC Voltaj	60.00mV/600.0mV/6.000V/60.00V/600.0V/1000V	$\pm(0.5\%+3)$
AC Voltaj	60.00mV/600.0mV/6.000V/60.00V/600.0V/750V	$\pm(1.0\%+3)$
DC Akım	60.00mA/600.0mA/6.000A/10.00A	$\pm(1.2\%+3)$
AC Akım	60.00mA/600.0mA/6.000A/10.00A	$\pm(1.5\%+3)$
Direnç	600.0 $\Omega$ /6.000k $\Omega$ /60.00k $\Omega$ /600.0k $\Omega$ /6.000M $\Omega$	$\pm(0.5\%+3)$
	60.00M $\Omega$	$\pm(1.5\%+3)$
Kapasite	9.999nF	$\pm(5.0\%+20)$
	99.99nF/999.9nF/9.999 $\mu$ F/99.99 $\mu$ F/999.9 $\mu$ F	$\pm(2.0\%+5)$
	9.999mF	$\pm(5.0\%+5)$
Frekans	99.99Hz/999.9Hz/9.999kHz/99.99kHz/	$\pm(0.1\%+2)$
	999.9kHz/9.999MHz	
Görev Döngüsü	1%-99%	$\pm(0.1\%+2)$
Diyot / Süreklilik	●/●	

<b>Özellikler</b>	TRUE RMS / Otomatik Kademe / Ekran Işıđı
	Düşük Pil Göstergesi / Deđer Sabitleme / Oto Kapanma
<b>Güç Kaynađı</b>	2 x 1.5V AAA Pil
<b>Boyut</b>	130*65*32mm
<b>Ađırlık</b>	114 gr