

Product Search Data Sheet

# DLW21SZ900HQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW21SZ900HQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21SZ900HQ2%23


### "#" indicates a package specification code.


In Production RoHS REACH

< List of part numbers with package codes > DLW21SZ900HQ2B DLW21SZ900HQ2L

### Appearance & Shape







- 1. Small size: 2.0x1.2x1.2mm
- 2. Common mode impedance items of 67, 90 and 120 ohm, and they can be used for various differential signal lines, DLW21SN\_HQ/DLW21SZ\_HQ/DLW21SR\_HQ series
- matches line impedance of 100 ohm line.
- 3. This series can suppress noise for the high-speed differential signal lines which are used in digital AVinterfaces, such as HDMI and DVI, without damage to the signal wave.
- 4. DLW21SR670HQ2 is designed to correct line impedance when ESD protection device is also used.

# Applications

Automotive Usage

Infotainment

## Packaging Information

Packaging	Specifications	Standard
		Packing
		Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	2000

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# DLW21SZ900HQ2#

Note: This datasheet may be out of date. Please download the latest datasheet of DLW21SZ900HQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21SZ900HQ2%23

### "#" indicates a package specification code.



### Specifications

Brand Murata

Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.2mm
Width Tolerance	±0.2mm
Thickness	1.2mm
Thickness Tolerance	±0.2mm
Common Mode Impedance (at 100MHz)	90Ω
Common Mode Impedance (at 100MHz) Tolerance	±25%
Rated Current	280mA
Derating of Rated Current	No
Rated Voltage	20Vdc
Withstanding Voltage	50Vdc
DC Resistance(max.)	0.41Ω
DC Resistance	0.41Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 105°C
Mass(typ.)	0.011g
Number of Circuit	1
Operating Temperature Range(Self-temperature rise is included)	No

2 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

- without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.








# DLW21SZ900HQ2#


Note: This datasheet may be out of date. Please download the latest datasheet of DLW21SZ900HQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-gb/products/productdetail?partno=DLW21SZ900HQ2%23

### "#" indicates a package specification code.







Impedance-Frequency Characteristics

Impedance-Frequency Characteristics (Main Items)


000

000

No Polarity.

 $(1) \bigcirc$ 

(4) C



Differential Mode Transmission Characteristics (Typical Value)

Equivalent Circuit

(2)

O (3)

3 of 3

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



<sup>2.</sup> This datasheet has only typical specifications because there is no space for detailed specifications.